

## 924-FB Soldering Flux

Low-Solids, No-Clean Liquid Flux

---

### Product Description

Kester 924-FB Soldering Flux is a non-rosin, organic flux designed for wave soldering conventional and surface mount circuit board assemblies. The very low solids content, surface tension properties and nature of the activator system results in practically no residue left on the assembly after soldering. Boards are dry and cosmetically clean as they exit the wave solder machine. There are no residues to interfere with electrical testing and the expense of cleaning is eliminated.

Although cleaning is eliminated, the flux will not harm the electrical reliability of the assembly. This non-corrosive and non-conductive flux meets the strictest requirements of Bellcore GR-78-CORE and ANSI/J-STD-004 specifications. 924-FB is suitable for automotive, computer, telecommunications and other applications where reliability considerations are critical. The surface insulation resistance on soldered boards is higher than provided by typical organic water soluble fluxes.

924-FB is suitable for soldering bare copper and solder coated circuit boards. Solder coated circuit boards are the preferred solderability protection for use of this flux. It is advised that bare copper boards be free of excessive oxides and other contamination for adequate soldering performance.

### Performance Characteristics:

- Essentially no residue left behind after soldering
- Eliminates the expense of cleaning
- Non-corrosive
- No surface insulation resistance degradation
- No offensive odors given off during soldering
- Uniform, stable foam head provided in foam fluxing equipment
- Compliant to GR-78-CORE
- Classified as ORL0 per J-STD-004

### RoHS Compliance

This product meets the requirements of the Restriction of Hazardous Substances (RoHS) Directive, 2011/65/EU for the stated banned substances.

**Physical Properties****Specific Gravity:** 0.801 + 0.005

Anton Paar DMA @ 25 °C

**Percent Solids (theoretical):** 4.1**Pounds per Gallon:** 6.68**Acid Number (typical):** 12.7 mg KOH/g flux

Tested by potentiometric titration

**pH (5% solution, typical):** 3.2

Mettler-Toledo MA235 pH/Ions Analyzer

**Thinner:** Kester 4662**Reliability Properties****Copper Mirror Corrosion:** Low

Tested to JIS-Z-3197

**Copper Corrosion:** Low

Tested to J-STD-004, IPC-TM-650, Method 2.6.15

**Surface Insulation Resistivity (SIR) Bellcore, IPC:** Pass

Tested to Bellcore TR-NWT-000078

	Blank	924-FB PD	924-FB PU
Day 4	$1.3 \times 10^{13} \Omega$	$2.2 \times 10^{13} \Omega$	$9.1 \times 10^{11} \Omega$
Day 11	$2.3 \times 10^{13} \Omega$	$1.4 \times 10^{13} \Omega$	$2.2 \times 10^{12} \Omega$

## Flux Application

924-FB can be applied to circuit board by foam and spray fluxing. The foam flux process will present a surface tension quality that will provide a stable, uniform head of small bubbles. To assure proper foaming action, filters and traps should be used on airlines to prevent dirt and excessive water from contaminating the flux. Flux deposition should be 120 to 240  $\mu\text{g}$  of solids/ $\text{cm}^2$  (750 to 1500  $\mu\text{g}$  of solids/ $\text{in}^2$ ). An air knife after the flux tank is recommended to remove excess flux from the circuit board and prevent dipping on the preheater surface. In a spray application it is suggested to inspect for even distribution across the bottom of the circuit board. Ensure the flux does not drip after it is applied to the circuit board.

## Process Considerations

The optimum preheat temperature for most circuit assemblies is 93 to 110  $^{\circ}\text{C}$  (200 to 230  $^{\circ}\text{F}$ ), as measured on the top of component side. Dwell time in the wave is typically 2 to 4 seconds for leaded solder alloys and 4 to 8 seconds for lead free alloys. The conveyor speed should be adjusted to accomplish proper contact time with the solder, then the temperatures of the preheat zone(s) should be adjusted to achieve the proper preheat temperatures..

## Flux Control

Control of the flux tank during use in a foam application is necessary to assure a consistent amount of flux is applied to the circuit boards, the least amount of residue remains after soldering, no interference in electrical probe testing and consistent soldering results are obtained. Due to the low solids of this flux (4.1%) a titration method is required to control the flux solids level in a foam application. The PS-22 test kit includes directions and solution required to perform this test. It will direct you as to how much 4662 flux thinner will need to be added. Testing should be done every 4 hours while the flux is exposed to air. This is not required in a spray application.

## Cleaning

924-FB residues are non-conductive, non-corrosive and do not require removal in most applications. If residue removal is required, call Kester Technical Support.

## Recycling Services

We provide safe and efficient recycling services to help companies meet their environmental and legislative requirements and at the same time, maximize the value of their waste streams.

Our service collects solder dross, solder scrap, and various forms of solder paste waste. Please contact your local sales representative for recycling capabilities in your area or [link here](#).



## Storage, Handling and Shelf Life

924-FB is flammable. Store away from sources of ignition. Shelf life is 1 year from the date of manufacture when handled properly and held at 10 to 25 °C (50 to 77°F).

## Health and Safety

This product, during handling or use, may be hazardous to your health or the environment. Read the Safety Data Sheet and warning label before using this product. Safety Data Sheets are available at this [link](#).

## Contact Information

To confirm this document is the most recent version, please contact [Assembly@MacDermidAlpha.com](mailto:Assembly@MacDermidAlpha.com)

<p><b>North America</b> 109 Corporate Blvd. South Plainfield, NJ 07080, USA 1.800.253.7837</p>	<p><b>Europe</b> Unit 2, Genesis Business Park Albert Drive Woking, Surrey, GU21 5RW, UK 44.01483.758400</p>	<p><b>Asia Pacific</b> 8/F., Paul Y. Centre 51 Hung To Road Kwun Tong, Kowloon, Hong Kong 852.3190.3100</p>
--	--	---

Also read carefully warning and safety information on the Safety Data Sheet. This data sheet contains technical information required for safe and economical operation of this product. READ IT THOROUGHLY PRIOR TO PRODUCT USE. Emergency safety directory assistance: US 1 202 464 2554, Europe + 44 1235 239 670, Asia + 65 3158 1074, Brazil 0800 707 7022 and 0800 172 020, Mexico 01800 002 1400 and (55) 5559 1588

DISCLAIMER: All statements, technical information and recommendations contained herein are based on tests we believe to be reliable, but the accuracy or completeness thereof is not guaranteed. No statement or recommendation shall constitute a representation unless set forth in an agreement signed by officers of seller and manufacturer. NO WARRANTY OF MERCHANTABILITY, WARRANTY OF FITNESS FOR A PARTICULAR PURPOSE OR ANY IMPLIED WARRANTY IS MADE. The following warranty is made in lieu of such warranties and all other warranties, express, implied, or statutory. Products are warranted to be free from defects in material and workmanship at the time sold. The sole obligation of seller and manufacturer under this warranty shall be to replace any noncompliant product at the time sold. Under no circumstances shall manufacturer or seller be liable for any loss, damage or expense, direct, indirect, incidental or consequential, arising out of the inability to use the product. Notwithstanding the foregoing, if products are supplied in response to a customer request that specifies operating parameters beyond those stated above, or if products are used under conditions exceeding said parameters, the customer by acceptance or use thereof assumes all risk of product failure and of all direct, indirect, incidental and consequential damages that may result from use of the products under such conditions, and agrees to exonerate, indemnify, defend and hold harmless MacDermid, Incorporated and its affiliates therefrom. No suggestion for product use nor anything contained herein shall be construed as a recommendation to use any product in a manner that infringes any patent or other intellectual property rights, and seller and manufacturer assume no responsibility or liability for any such infringement.

© 2019 MacDermid, Inc. and its group of companies. All rights reserved. "R" and "TM" are registered trademarks of MacDermid, Inc. and its group of companies in the United States and/or other countries.