

## 951 Soldering Flux

### Low-Solids No-Clean Liquid Flux

---

#### Product Description

Kester 951 is a halogen-free flux designed for wave soldering conventional and surface mount circuit board assemblies. The extremely low solids content (2.0%) and nature of the activator system results in practically no residue left on the assembly after soldering. Boards are dry and cosmetically clean as they exit the wave solder machine. There are no residues to interfere with electrical testing. 951 exhibits improved soldering performance to minimize solder bridges (shorts) and excessive solder defects. This flux is suitable for automotive, computer, telecommunications and other applications where reliability considerations are critical. 951 contains a corrosion inhibitor such that no corrosion products are formed when bare copper surfaces are exposed to humid environments.

#### Performance Characteristics:

- Improves soldering performance
- Eliminates the need and expense of cleaning
- Non-corrosive tack-free residues
- Classified as ORL0 per J-STD-004

#### RoHS Compliance

This product meets the requirements of the Restriction of Hazardous Substances (RoHS) Directive, 2015/863 for the stated banned substances.

#### Physical Properties

**Specific Gravity:** 0.814

Anton Paar DMA @ 25 °C

**Percent Solids (theoretical):** 2.0%

**Acid Number (typical):** 14.3 mg KOH/g flux

Tested by potentiometric titration

**Thinner:** 110

## Reliability Properties

**Copper Mirror Corrosion:** Low

Tested to J-STD-004, IPC-TM-650, Method 2.3.32

**Corrosion Test:** Low

Tested to J-STD-004, IPC-TM-650, Method 2.6.15

**Silver Chromate:** Pass

Tested to J-STD-004, IPC-TM-650, Method 2.3.33

**Chloride and Bromides:** None Detected

Tested to J-STD-004, IPC-TM-650, Method 2.3.35

**Fluorides by Spot Test:** Pass

Tested to J-STD-004, IPC-TM-650, Method 2.3.35.1

**Surface Insulation Resistivity (SIR), IPC (typical):** Pass

Tested to J-STD-004, IPC-TM-650, Method 2.6.3

	Blank	951PD	951PU
Day 1	$2.3 \times 10^{10} \Omega$	$9.4 \times 10^9 \Omega$	$8.2 \times 10^9 \Omega$
Day 4	$1.3 \times 10^{10} \Omega$	$7.8 \times 10^9 \Omega$	$7.5 \times 10^9 \Omega$
Day 7	$9.8 \times 10^9 \Omega$	$6.3 \times 10^9 \Omega$	$5.8 \times 10^9 \Omega$

## Flux Application

951 can be applied to circuit boards by a spray, foam or dip process. Flux deposition should be 120 to 240µg of solids/cm<sup>2</sup> (750 to 1500µg of solids/in<sup>2</sup>). An air knife after the flux tank is recommended to remove excess flux from the circuit board and prevent dripping on the preheater surface when used in a foam or wave application.

## Process Considerations

The optimum preheat temperature for most circuit assemblies is 93 to 115 °C (200 to 230 °F) as measured on the top or component side of the printed circuit board. Dwell time in the wave is typically 2 to 4 seconds for leaded alloys and 4 to 8 seconds for lead-free alloys. The conveyor speed should be adjusted to accomplish proper board contact time with the solder. Then the preheat temperatures are adjusted to achieve the required preheat top board temperatures. In the event you need further direction on the setup of your wave soldering system, please contact Kester Technical Support.

## Flux Control

Acid number is normally the most reliable method to control the flux concentration of low solids, no-clean fluxes. To check concentration, a simple acid-base titration should be used. PS-22 Test Kit and procedure are available from Kester. Control of the flux in the foam flux tank during use is necessary for assurance of consistent flux distribution on the circuit boards. The complex nature of the solvent system for the flux makes it imperative that Kester 110 Thinner be used to replace evaporative losses. When excessive debris from circuit boards, such as board fibers and from the airline build up in the flux tank, these particulates will redeposit on the circuit boards which may create a buildup of residues on probe test pins. It is, therefore, necessary to clean the tank and then replenish it with fresh flux when excessive debris accumulates in the flux tank.

## Cleaning

951 flux residues are non-conductive, non-corrosive and do not require removal in most applications. If residue removal is required, call Kester Technical Support.

## Storage, Handling and Shelf Life

951 is flammable. Store away from sources of ignition. Shelf life is 1 year from the date of manufacture when handled properly and held at 10 to 25 °C (50 to 77 °F). The cap must be in place when not being used.

## Health and Safety

This product, during handling or use, may be hazardous to your health or the environment. Read the Safety Data Sheet and warning label before using this product. Safety Data Sheets are available at <https://www.kester.com/downloads/sds>.

## Contact Information

To confirm this document is the most recent version, please contact  
[Assembly@MacDermidAlpha.com](mailto:Assembly@MacDermidAlpha.com)

<b>North America</b> 800 West Thorndale Avenue Itasca, IL USA 60143  Phone: +1 800.2.KESTER	<b>Asia Pacific</b> 61 Ubi Avenue 1 #06-01 UB Point Singapore 408941  Phone: +65 6.449.1133	<b>Europe</b> Ganghofer Strasse 45 82216 Gernlinden, Germany  Phone: +49 (0) 8142 4785 0
---	--	--

Also read carefully warning and safety information on the Safety Data Sheet. This data sheet contains technical information required for safe and economical operation of this product. READ IT THOROUGHLY PRIOR TO PRODUCT USE. Emergency safety directory assistance: US 1 202 464 2554, Europe + 44 1235 239 670, Asia + 65 3158 1074, Brazil 0800 707 7022 and 0800 172 020, Mexico 01800 002 1400 and (55) 5559 1588

DISCLAIMER: All statements, technical information and recommendations contained herein are based on tests we believe to be reliable, but the accuracy or completeness thereof is not guaranteed. No statement or recommendation shall constitute a representation unless set forth in an agreement signed by officers of seller and manufacturer. NO WARRANTY OF MERCHANTABILITY, WARRANTY OF FITNESS FOR A PARTICULAR PURPOSE OR ANY IMPLIED WARRANTY IS MADE. The following warranty is made in lieu of such warranties and all other warranties, express, implied, or statutory. Products are warranted to be free from defects in material and workmanship at the time sold. The sole obligation of seller and manufacturer under this warranty shall be to replace any noncompliant product at the time sold. Under no circumstances shall manufacturer or seller be liable for any loss, damage or expense, direct, indirect, incidental or consequential, arising out of the inability to use the product. Notwithstanding the foregoing, if products are supplied in response to a customer request that specifies operating parameters beyond those stated above, or if products are used under conditions exceeding said parameters, the customer by acceptance or use thereof assumes all risk of product failure and of all direct, indirect, incidental and consequential damages that may result from use of the products under such conditions, and agrees to exonerate, indemnify, defend and hold harmless MacDermid, Incorporated and its affiliates therefrom. No suggestion for product use nor anything contained herein shall be construed as a recommendation to use any product in a manner that infringes any patent or other intellectual property rights, and seller and manufacturer assume no responsibility or liability for any such infringement.

© 2019 MacDermid, Inc. and its group of companies. All rights reserved. "®" and "TM" are registered trademarks of MacDermid, Inc. and its group of companies in the United States and/or other countries.